

## 48290504

# Solid current sensor TE-45 45mm 160-630A



#### Strong points

- Plug & Play
- Accuracy as per standard IEC 61557-12
- Installation

#### General characteristics

- Range from 5 to 2000A.
- used with DIRIS Digiware, DIRIS A-40 and DIRIS B.

#### Compliance with standards

- IEC 61557-12
- ISO 14025
- UL

## Link to the reference

2024-04-26 23:45:30



https://apac.socomec.com/en/reference/ 48290504

TE smart current sensors measure the load currents of an electrical system and send the data to meters and measurement hubs via an RJ12 plug-and-play output. Thanks to a wide measurement range, TE current sensors cover the full current range of 5 to 2000 A, with 7 references. TE solid current sensors can be connected to DIRIS Digiware, DIRIS A-40 and DIRIS B via a rapid RJ12 connection. Numerous accessories are available to aid the installation of sensors in any type of cabinet.

Fill rate E-Order Common	29
Fill rate E-Order Selection	100
Classification	
JNSPSC	83101808
ETIM Class	EC002048
GCC	6042
Commerce	
Effective date	2013-11-22
Country of origin	FR
Discount Policy	1EN30
Discount Policy Label	SENSORS
ETIM - Electrical characteristics	
Rated primary current [A]	630
Rated secondary current [A]	0.1
Rated secondary apparent power [VA]	0.1
Accuracy class	0.2\$
Overcurrent limiting factor	FS 10
Calibrated	Yes
ETIM - Mechanical characteristics	
With contact protection	Yes
Height opening [mm]	3131
Nidth opening [mm]	3131
Opening diameter [mm]	31
Snap mounting	Yes
With copper rail	Yes
Secondary connection	Plug-in connection
ETIM - Technical features	
Model	Through-feed current converter
Number of primary inputs	1
ogistics	
GTIN/EAN	3596032776503
Customs number	8504312990
Price unit	PC
Weight of the packing unit	0.17
ength of the packing unit	0.1
Nidth of the packing unit	0.06
Depth of the packing unit	0.04
Norms	
Conformity to standards	IEC br/>UL

2024-04-26 23:45:30 2/3



## **Technical Characteristics**

Model	TE
Opening	31x31
Rated current	630
Secondary rated current	RJ12

2024-04-26 23:45:30 3/3