

## 21PV6722

# Load break switch photovoltaic applications SIRCO MC PV 1000VDC 2x(1P+, 1P-) 25A



SIRCO MC PV are DC load break switches. They make and break under load conditions and provide optimum safety isolation for any PV circuit.

### Strong points

- Compact
- High breaking capacity up to 1000 VDC
- Safety
- Easy mounting

### General characteristics

- Range from 25A to 40A.
- Up to 1000 VDC.
- Din-rail mounting or door mounted.

#### Compliance with standards

- IEC 60947-3
- UL508i

### Link to the reference

https://apac.socomec.com/en/reference/21PV6722

Classification	
UNSPSC	39122233
ETIM Class	EC000216
IGCC	5290
Commerce	
Effective date	2012-09-10
Country of origin	PL
Length of the product unit	0.078
Width of the product unit	0.052
Depth of the product unit	0.0675
Weight	0.351
ETIM - Electrical characteristics	
Max. rated operation voltage Ue AC [V]	1000
Rated operating voltage [V]	6001000
Rated permanent current lu [A]	25
Number of poles	3
ETIM - Mechanical characteristics	
Suitable for floor mounting	No
Suitable for front mounting 4-hole	Yes
Suitable for front mounting centre	No
Suitable for distribution board installation	Yes
Suitable for intermediate mounting	Yes
Colour control element	Other
Degree of protection (IP), front side	IP20
ETIM - Technical features	
Version as main switch	Yes
Version as maintenance-/service switch	Yes
Version as safety switch	Yes
Version as emergency stop installation	Yes
Version as reversing switch	No
Number of switches	1
Motor drive optional	No
Motor drive integrated	No
Voltage release optional	No
Device construction	Built-in device fixed built-in technique
Type of control element	Other
Interlockable	Yes
Type of electrical connection of main circuit	Screw connection
Logistics	
GTIN/EAN	3596032697624
Customs number	8536508090
Price unit	PC
Weight of the packing unit	0.351
Length of the packing unit	0.095

2024-05-06 12:16:51





Width of the packing unit	0.12	
Depth of the packing unit	0.1	
Norms		
Conformity to standards	IEC br/>UL	
Technical Characteristics		
Control operator	Manual	
Number of poles	3+3	
Rated voltage	1000	
Rated current	25	
Туре	Frontal operation	
Frame size	MC	

2/024-05-06 12:16:51