

## 36606064

# Switch-discon-fuse visi break FUSOMAT ST coil-Ext&Dir F OP-630A-4P-BS-Fuse C1-C2

### Strong points

- Overload tripping
- High breaking capacity
- Improved safety

#### General characteristics

- 250 A to 1250 A.
- 3P or 4P available.
- Direct or external handle.
- Auxiliary contact optional.

#### Compliance with standards

- IEC 60947-3

#### Link to the reference

https://apac.socomec.com/en/reference/ 36606064 FUSOMAT fuse-combination switches are manually operated 3 or 4-pole load break switches with visible breaking and a remote tripping function.

They provide load operation, safety disconnection and protection against overloads and short-circuits in any low voltage electrical circuit. They can ensure the automatic opening of the circuit together with:

- Fuse blown detection system
- thermal relay
- Differential relay
- other safety devices

Motor drive optional

Logistics GTIN/EAN

Price unit

Customs number

Weight of the packing unit

Motor drive integrated

Version as emergency stop installation

UNSPSC	39122233
ETIM Class	EC001040
IGCC	5291
Commerce	
Effective date	1992-09-11
Obsolescence date	2023-06-30
Production ban date	2023-12-30
Country of origin	FR
ETIM - Electrical characteristics	
Max. rated operation voltage Ue AC [V]	690
Rated permanent current lu [A]	630
Rated operation power at AC-23, 400 V [kW]	355
Conditioned rated short-circuit current Iq [kA]	100
Number of poles	4
ETIM - Mechanical characteristics	
Cable entry	Top/bottom
Equipped with connectors	No
Suitable for floor mounting	Yes
Suitable for front mounting	Yes
Suitable for busbar mounting	No
Degree of protection (IP), front side	IP20
ETIM - Technical features	
Version as main switch	Yes
Version as safety switch	Yes
	Shape C1-C3
Suitable for fuses	
	No
Suitable for fuses With error protection Type of electrical connection of main circuit	No Bolt connection

No No

Yes

19

3596031186228

8536309090 PC



Length of the packing unit	0.6
Width of the packing unit	0.6
Depth of the packing unit	0.8
Norms	
Conformity to standards	IEC
Technical Characteristics	
Fuse size	C1-C2
Number of poles	4
Rated current	630